

Through outlet bridged 2 connectors: FM/TV-SAT

Through outlet bridged equipped with two IEC connectors (male on the left, female on the right) with TV+SAT outputs. It is bridged and therefore the full FM, TV and SAT input signal is available on both connectors.
Equipped with signal pass-through, which allows the series connection of multiple outlets.

Ref.	4335
EAN13	8424450043356

Other features	
Complement	Outlet + Faceplate + Baseboard

Packaging info	
Blister	1 pcs.
Box	8 pcs.
Bucket	32 pcs.

Physical data	
Net weight	100.00 g
Gross volume	0.99 dm³
Gross weight	100.00 g
Width	80.00 mm
Height	80.00 mm
Depth	32.00 mm
Main product weight	130.00 g

Highlights

- High shielding
- Robot-controlled automated manufacturing
- Made of Zamak, high strength
- Compatible with coaxial cable with sheath diameters in the 5-to-6,9 mm range (Ø 5...6,9 mm)

Discover

Televes outlets: Screw-free mounting

A class A outlet offering numerous advantages:

- The inner conductor is connected simply by pushing, without the need for screws; still the gripping force is equivalent
- Supports inner conductor diameters from 0.65 mm to 1.2 mm, and external cable diameters from 5 mm to 6.9 mm
- F-connector type conic guide for easy inner conductor introduction
- Wide margin in inner conductor length (from 5 mm to 15 mm), which makes short circuits between core and mesh difficult
- Tilt-up, self-supporting, full-opening clamp
- The clamp is equipped with 3 jagged rows in 9 mm for a perfect braid fixing
- Printed circuit board perforation to make the faceplate fixing screw compatible
- Rounded edges to prevent cuts
- Class A shielding

Furthermore, this product range includes several engravings on the chassis:

- CE marking
- Numerical and logical references
- Input and output indications
- Cable stripping dimensions

Technical specifications : Ref. 4335

Fastening method		Without screws	
Number of connectors		2	
R/TV Connector		"IEC" male	
SAT Connector		"IEC" female	
Pass-through output		Yes	
Bands		TV	SAT
Frequency range	MHz	5 ... 862	950 ... 2400
Through losses	dB	1	1
Attenuation: R/TV Connector	dB	1	--
Attenuation: SAT Connector	dB	--	1
DC pass		SAT In / Out In	
Max. current	mA	350	