



## Through outlet bridged 2 connectors: FM/TV-SAT

Through outlet bridged equipped with two IEC connectors (male on the left, female on the right) with TV+SAT outputs.

It is bridged and therefore the full FM, TV and SAT input signal is available on both connectors.

Equipped with signal pass-through, which allows the series connection of multiple outlets.

|              |               |
|--------------|---------------|
| <b>Ref.</b>  | 5270          |
| <b>EAN13</b> | 8424450052709 |

### Other features

|                   |        |
|-------------------|--------|
| <b>Complement</b> | Outlet |
|-------------------|--------|

### Packaging info

|               |           |
|---------------|-----------|
| <b>Box</b>    | 1 pcs.    |
| <b>Carton</b> | 10 pcs.   |
| <b>Pallet</b> | 3600 pcs. |

### Physical data

|                            |          |
|----------------------------|----------|
| <b>Net weight</b>          | 100.00 g |
| <b>Gross volume</b>        | 0.20 dm³ |
| <b>Gross weight</b>        | 100.00 g |
| <b>Width</b>               | 70.00 mm |
| <b>Height</b>              | 70.00 mm |
| <b>Depth</b>               | 27.00 mm |
| <b>Main product weight</b> | 89.00 g  |

### Highlights

- High shielding
- Robot-controlled automated manufacturing

- Made of Zamak, high strength
- Compatible with coaxial cable with sheath diameters in the 5-to-6,9 mm range (Ø 5...6,9 mm)

## Discover

---

### **Televes outlets: Screw-free mounting**

A class A outlet offering numerous advantages:

- The inner conductor is connected simply by pushing, without the need for screws; still the gripping force is equivalent
- Supports inner conductor diameters from 0.65 mm to 1.2 mm, and external cable diameters from 5 mm to 6.9 mm
- F-connector type conic guide for easy inner conductor introduction
- Wide margin in inner conductor length (from 5 mm to 15 mm), which makes short circuits between core and mesh difficult
- Tilt-up, self-supporting, full-opening clamp
- The clamp is equipped with 3 jagged rows in 9 mm for a perfect braid fixing
- Printed circuit board perforation to make the faceplate fixing screw compatible
- Rounded edges to prevent cuts
- Class A shielding

Furthermore, this product range includes several engravings on the chassis:

- CE marking
- Numerical and logical references
- Input and output indications
- Cable stripping dimensions

## Technical specifications : Ref. 5270

|                             |     |           |                 |              |
|-----------------------------|-----|-----------|-----------------|--------------|
| Fastening method            |     |           | Without screws  |              |
| Number of connectors        |     |           | 2               |              |
| R/TV Connector              |     |           | "IEC" male      |              |
| SAT Connector               |     |           | "IEC" female    |              |
| Pass-through output         |     |           | Yes             |              |
| Bands                       |     |           |                 |              |
| Frequency range             | MHz | TV        |                 | SAT          |
|                             |     | 5 ... 862 |                 | 950 ... 2400 |
| Through losses              | dB  | 1         |                 | 1            |
| Attenuation: R/TV Connector | dB  | 1         |                 | --           |
| Attenuation: SAT Connector  | dB  | --        |                 | 1            |
| DC pass                     |     |           | SAT□In / Out□In |              |
| Max. current                | mA  |           | 350             |              |