F 8W terminal tap 5...2400MHz 14dB



8-way tap with F connectors, for SMATV signals. Its tap losses (14dB) as well as the lack of pass output, make it suitable for installation in floor 1.

It presents a high efficient electrical behavior thanks to the miniaturization applied in the electronic components included. In addition, its Zamak chassis provides great shielding.

It is conceived for indoor installation, for wall, rack plate or standard DIN rail assembly.
Supplied in 10-unit boxes.

Ref.	519382
Logical ref.	AZS812FZ
EAN13	8424450268001

Packaging info	
Box	10 pcs.

Physical data	
Net weight	131.00 g
Gross volume	0.17 dm³
Gross weight	131.00 g
Width	176.00 mm
Height	54.00 mm
Depth	18.00 mm

Highlights

- Assembly flexibility: it can be installed screwed to the wall, on rack plates with nuts on their connectors, or on a standard DIN rail (with adapter ref. 519901)
- Comfortable screwing of the cable, thanks to a 10º inclination angle of the F-connectors from the installation wall
- Space optimization in registers and cabinets: their inputs/outputs are always located on the same side
- Better organization of the installation: allows cabling passage through its rear part

- F-Series elements can be chained between them with the ground screw, requiring in this case a single grounding cable
- Signal level is maintained in outlets, even with long cable deployment, thanks to a better flatness response
- Outstanding reliability: robotized manufacturing using new generation micro-components
- Great shielding (class A), made of Zamak
- F connectors with a longer threaded length, to facilitate and secure the installation on a rack plate
- Indoors installation
- Ground screw included
- Does not have any pass outputs
- 100% European design, quality and manufacturing

Technical specifications : Ref. 519382

Frequency range	MHz	5 ... 2400	
Number of outputs		8	
Floors		1	
Inputs/Bands		TERR	SAT
Tap losses	dB	15	14
Rejection between taps	dB	> 20	> 20
Connectors		"F" female	