


REPARTIDORES/DERIVADORES "F" SMATV

ESPECIFICACIONES TÉCNICAS



REPARTIDORES			519502	519503	519504	519505	519506	519508
Salidas			2	3	4	5	6	8
Margen de frecuencia		MHz	5...2400		5...2400		5...2400	
Pérdidas de paso	MATV (5-862MHz)	dB	5	8	9	11	12	15
	SAT (950-2400 MHz)		4	7	8	10	11	14
Aislamiento	SMATV (5-2400MHz)	dB	>20		>20		>20	
Corriente máx. [Salida→Entrada]		mA	350		350		350	
Medidas exteriores (xyz)		mm	74x54x18		109x54x18		176x54x18	



REPARTIDORES + PAU			519532	519533	519534	519535	519536
Salidas			2	3	4	5	6
Margen de frecuencia		MHz	5...2400	5...2400		5...2400	
Pérdidas de paso	MATV (5-862MHz)	dB	5	8	9	11	12
	SAT (950-2400 MHz)		4	7	8	10	11
Aislamiento	SMATV (5-2400MHz)	dB	>20	>20		>20	
Corriente máx. [Salida→Entrada]		mA	350	350		350	
Medidas exteriores (xyz)		mm	74x54x18	109x54x18		176x54x18	



DERIVADORES			519322	519323	519324	519325	519341	519342	519343	519344	519345
Derivaciones			2				4				
Margen de frecuencia		MHz	5...2400				5...2400				
Pérdidas de derivación	MATV (5-862MHz)	dB	12	16	20	24	8,5	13	17	20,5	23,2
	SAT (950-2400 MHz)		11	15	19	23	9	12,5	17,5	20	23,5
Pérdidas de paso	MATV (5-862MHz)	dB	2,3	2	1,5	1,5	--	2,5	2,5	2,2	2,3
	SAT (950-2400 MHz)		3,4	2,5	2	2	--	3,6	3	2,2	2,5
Aislamiento	SMATV (5-2400MHz)	dB	>20				>20				
Corriente máx. [Entrada↔Salida paso]		mA	350				--	350			
Medidas exteriores (xyz)		mm	74x54x18				109x54x18				



			519362	519363	519364	519365	519382	519383	519384	519385
Derivaciones			6				8			
Margen de frecuencia		MHz	5...2400				5...2400			
Pérdidas de derivación	MATV [5-862MHz]	dB	12	17	20	24	15	17,5	20	24,5
	SAT [950-2400 MHz]		11,5	18	21,5	25	14	16,5	20	23,5
Pérdidas de paso	MATV [5-862MHz]	dB	--	5	3	2	--	5,5	4,5	2,2
	SAT [950-2400 MHz]		--	5	4	3	--	6,7	5	2,7
Aislamiento	SMATV [5-2400MHz]	dB	>20				>20			
Corriente máx. [Entrada ←→Salida paso]		mA	--	350			--	350		
Medidas exteriores (xyz)		mm	176x54x18				176x54x18			

