

NANOKOM MASTHEAD AMPLIFIER

3 INPUTS: UHF-UHF-IFmix




REF.	ART. NR.	DESCRIPTION	EAN 13
561401	MVMS32DCLTE	MAST AMP.12...24V 3I/1O UHF-UHF-SATmix	8424450186268



Nanokom masthead amplifier with **3 inputs (UHF1, UHF2, SAT)**, appropriate for areas where is necessary to use more than one UHF antenna.

- **High output power and gain** in UHF.
- Integrated **anti LTE filter** (C21 - C59).
- **Very low noise figure**.
- ON/OFF switch for **DC pass** in one UHF input.
- Aesthetic and **ultra-small** design.
- **"Easy F"** connection system, reliable and safe, saving up to 50% of the installation time.
- Resistant ABS-plastic case for outdoor installation.



REF.	ART. NR.	 mm (xyz)	 g	 U./Pack.
561401	MVMS32DCLTE	88x79x42	220	1 / box



Ref. Art. Nr.		561401 MVMS32DCLTE		
Inputs/Bands		UHF 1	UHF 2	SAT
Frequency range	MHz	470...782	470...782	950...2150
Gain	dB	28		-2,5
Gain regulation margin	dB	MANUAL 0...20		-
Output level	EN50083	115		-
	DIN45004B	108		-
Noise figure	dB	6,5		-
DC Pass	DC UHF	OFF	0	
		ON	40	
	DC SAT	-		300
Powering / Current consumption	Vdc/mA	12 - 24 / 50		
Protection index	IP	23		
Operating temperature	°C	-5...+45		

